

## **APC Smart-UPS X-Series 48V External Battery Pack Rack/Tower**

SMX48RMBP2U



• Includes: Installation guide, Rack mounting brackets

| Output                 |      |
|------------------------|------|
| Battery Output Voltage | 48 V |

| Input                 |       |  |
|-----------------------|-------|--|
| Nominal Input Voltage | 48VDC |  |

| Batteries & Runtime           |                            |
|-------------------------------|----------------------------|
| Battery type                  | Lead-acid battery          |
| Battery mounting              | Enclosed battery cartridge |
| Expected Battery Life (years) | 3 - 5                      |
| RBC Quantity                  | 2                          |

| Physical        |               |
|-----------------|---------------|
| Maximum Height  | 89MM, 8.9CM   |
| Maximum Width   | 432MM, 43.2CM |
| Maximum Depth   | 490MM, 49.0CM |
| Rack Height     | 2U            |
| Net Weight      | 28.64KG       |
| Shipping weight | 35.5KG        |
| Shipping Height | 246MM, 24.6CM |
| Shipping Width  | 589MM, 58.9CM |
| Shipping Depth  | 620MM, 62.0CM |
| Color           | Black         |

**Disclaimer:** Documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user's applications.

## **Technical Specifications**



APC Smart-UPS X-Series 48V External Battery Pack Rack/Tower | SMX48RMBP2U | Downloaded on 01/25/2021 (EST)

| Physical         |     |
|------------------|-----|
| Units per Pallet | 8.0 |

| Conformance       |                           |
|-------------------|---------------------------|
| Standard warranty | 2 years repair or replace |

| Sustainable Offer Status |                                |
|--------------------------|--------------------------------|
| RoHS                     | Compliant                      |
| PEP                      | Available in Documentation tab |
| EOLI                     | Available in Documentation tab |
| Proposition 65 Warning   | Available in Documentation tab |

Disclaimer: Documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user's applications.